ELSEVIER

Frontiers

Contents lists available at ScienceDirect

Chaos, Solitons and Fractals

Nonlinear Science, and Nonequilibrium and Complex Phenomena

journal homepage: www.elsevier.com/locate/chaos

Dynamics of non-autonomous oscillator with a controlled phase and frequency of external forcing



D.A. Krylosova^b, E.P. Seleznev^{a,b}, N.V. Stankevich^{a,c,d,*}

^a Kotel'nikov's Institute of Radio-Engineering and Electronics of RAS, Saratov Branch, Zelenaya 38, Saratov 410019, Russia

^b Saratov State University, Astrakhanskaya, 83 410012, Russia

^c Yuri Gagarin State Technical University of Saratov, Politehnicheskaya 77, Saratov 410054, Russia

^d St.Petersburg State University, Universitetskiy proezd, 28, Peterhof 198504, Russia

A R T I C L E I N F O

Article history: Received 7 August 2019 Revised 9 February 2020 Accepted 26 February 2020

Keywords: Non-autonomous oscillator Sinusoidal-nonlinearity Chaos Adaptation

ABSTRACT

The dynamics of a non-autonomous oscillator in which the phase and frequency of the external force depend on the dynamical variable is studied. Such a control of the phase and frequency of the external force leads to the appearance of complex chaotic dynamics in the behavior of oscillator. A hierarchy of various periodic and chaotic oscillations is observed. The structure of the space of control parameters is studied. It is shown there are oscillatory modes similar to those of a non-autonomous oscillator with a potential in the form of a periodic function in the system dynamics, but there are also significant differences. Physical experiments of such systems are implemented.

© 2020 Elsevier Ltd. All rights reserved.

1. Introduction

Many systems, including radiophysical, biological, and others, exhibit oscillatory processes in which one the system acts on another with a periodic signal, but when the operating conditions change, the frequency of forcing changes. For example, in information transmission systems to ensure high stability, the so-called phase-locked loop is used [1–4]. The system of cardiovascular regulation of living organisms with a change in load increases or decreases the heart rate [5–9]. Such property for neurons can explain plasticity and memory [10–13]. In some assumption such phenomena can be called and interpreted as adaptation. In such interactions, the dependence of the phase or frequency on the dynamic variable can lead to the appearance of complex dynamics in the system. The control process in this case is challenge task, its research and modeling encounters a number of difficulties. One of the ways in the study of such systems and processes is the consideration of simpler objects in which the excitation of oscillations and frequency control are rather easily modeled. As such a system, it is convenient to use the classical model of the theory of oscillations

A simple object for studying adaptation properties can be simple self-oscillating model, such as a harmonic oscillator, which is a paradigmatic model that characterizes a wide range of systems in

* Corresponding author. E-mail address: stankevichny@mail.ru (N.V. Stankevich).

https://doi.org/10.1016/j.chaos.2020.109716 0960-0779/© 2020 Elsevier Ltd. All rights reserved. engineering and natural sciences [14-15]. A dissipative linear oscillator with external force (non-autonomous) in the simplest case demonstrates self-oscillations or a stable equilibrium state as an attractor. The complication of the dynamics of such a system is traditionally observed with the addition of nonlinear terms. For example, adding cubic nonlinearity will result in the well-known Duffing oscillator [16-21]. In [22-24] were presented modifications of Duffing oscillator describing a mechanical system with friction, which can demonstrate chaotic behavior. These results were verified by numerical simulations and theoretical approaches [20, 22-24]. Another modified non-autonomous Duffing oscillator allows to describe complex bursting dynamics [25]. By adding exponential nonlinearity, we get a Toda oscillator [26-27], whose equation reproduces the dynamics of the RL-diode circuit [28-31]. When such systems interact, they exhibit complex dynamic behavior, including chaos, quasiperiodic oscillations, multistability, nonlinear resonance, etc. [32-40]. Another interesting option is oscillator with nonlinearity of the sine type. It is one of the reference models of nonlinear dynamics [15]. It describes the oscillations of a mathematical and physical pendulum, and also appears in other applied problems, for example, when considering Josephson contact [41-44], when studying self-induced transparency in nonlinear optics, when analyzing the bending of an elastic beam. Also such kind of models can occur in electromechanical systems [45]. Dynamical systems of this type have very rich dynamics [46–50]. The richness of the dynamics of such oscillators is related to the form of the potential function, which is periodic and has an infinite number of maxima and minima. In the case of a symmetric potential function, dynamics is observed, accompanied by a transition from one well to another. In addition to the well-known scenarios of transition to chaos and types of bifurcations, so-called metastable chaos takes place in such systems. In the case of asymmetry of the potential function, the so-called particle drift in the periodic potential is observed.

In the frame of this work, we consider the features of the system when the external signal is complicated, i.e. taking into account the dependence of the phase and frequency of external influence on the dynamic variable. The accounting of adaptive properties in such a model can lead to the appearance of complex oscillatory regimes. A study of the dynamics of a non-autonomous oscillator with a controlled phase and frequency of external force is presented. The structure of the space of control parameters is investigated. The role of parameters is determined. The work is structured as follows. In Section 2 we describe the object of study: a linear oscillator with an external periodic force, the external force of which has a phase dependent on a dynamical variable, which leads to the appearance of nonlinearity in the system. We discuss in detail the dynamics of the oscillator, the phase of which depends on the dynamical variable. In Section 3 we presents a model of harmonic oscillator with frequency depending on the state of oscillator and the numerical study of this model. In Section 4 we present implementation of proposed model in physical experiment and compare numerical and experimental results.

2. Harmonic oscillator under external periodic force with a controlled phase

As the simplest object of study, we will choose the classical model of the theory of oscillations [14,15] - RLC - circuit, excited by an external signal, which is written in the following form¹:

$$\ddot{x} + \alpha \dot{x} + x = A \text{Sin}(p\tau + \phi), \tag{1}$$

where x, \dot{x} are dimensionless dynamic variables, α is dissipation coefficient, A and ϕ are amplitude and phase of the external force, $p = \omega/\omega_0$ is normalized frequency of external force, this coefficient characterizes ration of natural circuit frequency and frequency of external force. Eq. (1) describes the behavior of a linear non-autonomous oscillator, the dynamics of which well known: the external force in such a system excites periodic self-oscillations [14, 15].

The first proposed modification of the model corresponds to the case when the phase of external force depends on the variable. The dependence of the phase on the variable is the simplest one, i.e. through a linear function:

$$\phi(\mathbf{x}) = k\mathbf{x},\tag{2}$$

where k is a constant coefficient. After the transition Eq. (1) takes the form:

$$\ddot{x} + \alpha \dot{x} + x = A \text{Sin}(p\tau + kx). \tag{3}$$

As result of modification, the Eq. (1) becomes non-linear and Eq. (3) contains a nonlinearity of type Sin(kx).

Thus, by controlling the phase of the external force, the linear equation describing the forced oscillations of the linear oscillator is also converted into a nonlinear one with nonlinearity of the Sin(kx)-type.

The analysis of the nature of the forced oscillations in the work was carried out on the basis of an assessment of the spectrum of Lyapunov exponents [51], which was calculated with Benettin algorithm [52], as well as on the analysis of phase portraits in the

stroboscopic section. The amplitude *A*, normalized frequency *p*, and phase control coefficient *k* were used as control parameters. For stability analysis, Eq. (3) was transformed into a system of three first-order differential equations:

$$\begin{aligned} x &= y, \\ \dot{y} &= -\alpha y - x + A \text{Sin}(z), \\ \dot{z} &= p + k y. \end{aligned}$$
 (4)

We study the characteristic structure of various parameter planes in this case.

Fig. 1 presents a charts of the dynamic regimes of system (4) on the plane of parameters (k, A) for three different values of the frequency of forcing p. Different colors denote the domains of periodic regimes with different periods, domains of chaotic oscillations, when the largest Lyapunov exponent is positive are depicted by gray color; the corresponding color palette is presented in the bottom of Fig. 1. Fig. 1a illustrates the structure of the parameter plane (k, A) at p = 0.25. In the dynamics of system (4), a sequence of period doubling bifurcations is observed, ending with a transition to chaos. In the region of the existence of chaos, its development is observed, associated with a decrease in the connectivity of the chaotic attractor, alternating with the appearance of zones of periodic oscillations. Fig. 1b illustrates the structure of the parameter plane (k, A) at p = 1. The structure of the parameter plane remains qualitatively unchanged, only the bifurcation values of the parameters A and k change. Fig. 1c illustrates the structure of the parameter plane (k, A) at p = 5. In general, the plane structure also represents an alternation of zones of periodic and chaotic oscillations. However, bands of periodic regimes corresponding to higher resonances appear. As can be seen from Fig. 1, an increase in the parameters A and k leads to a qualitatively identical change in the dynamics of the system.

Fig. 2 shows two-dimensional projections of phase portraits illustrating the appearance of a chaotic attractor as a result of a cascade of period doubling bifurcations, stroboscopic section of phase portrait is depicted by blue points. Fig. 2a shows the limit cycle for small values of the parameters of the amplitude of the external signal and coefficient k. With an increase in the amplitude of the external force, the limit cycle increases in size (Fig. 2b). As the coefficient k increases, the shape of the limit cycle changes, additional loops appear (Fig. 2c), however, in the stroboscopic section, this attractor still corresponds to a single fixed point. Fig. 1d shows an example of a more complex attractor for large values of the parameters A and k. On the basis of such a limit cycle, a cascade of period doubling bifurcations occurs in the system. In Fig. 2e, an example of a double limit cycle is shown, and then the chaos develops, presented in Fig. 2e. Inside the chaos region with a further increase in the parameters on the parameter plane, periodicity windows are observed, inside which a cascade of period doubling bifurcations also occurs and chaos also appears. For all cases shown in Fig. 2, the dynamics of the system develops in the vicinity of one of the potential wells located on one side of the unstable zero equilibrium state. In this case, the phase trajectory can also enter the region of the second symmetric potential well, but then returns. This is clearly seen in the stroboscopic sections, which are located in the negative region of the dynamical variable *x*.

A similar scenario is observed with increasing frequency parameter p. However, with increasing frequency, attractor grows in size and begins to visit other potential wells that are more distant from the zero equilibrium state. At the same time, dynamic chaos developing at various frequencies has its own characteristic features. To analyze the features, stroboscopic sections of phase portraits and Fourier spectra for chaotic attractors were constructed for various values of the parameter p, which are presented in Fig. 3.

For small values of the parameter p, which is responsible for the frequency of the external force (p = 0.25), the oscillator dynam-

¹ Transformation of equations from non-autonomous *RLC*-circuit to dimensionless form presented in Appendix



Fig. 1. Charts of dynamical modes of harmonic oscillator under external periodic force with a controlled phase (4) for $\alpha = 0.1$, a) p = 0.25, b) p = 1, c) p = 5.



Fig. 2. Two-dimensional projections of phase portraits (red lines) and cross-sectional stroboscopic sections (blue dots) of harmonic oscillator under external periodic force with a controlled phase (4) for various points of the parameter plane (k, A) at p = 0.25. a) k = 0.1, A = 0.5; b) k = 0.3, A = 0.5; c) k = 0.3, A = 0.75; d) k = 0.32, A = 2.67; e) k = 0.36, A = 3.07; f) k = 0.62, A = 5.85.

ics mainly develops in one of the potential wells close to the zero equilibrium point. The peak corresponding to the base frequency of the limit cycle from which this chaotic attractor was born is clearly visible in the Fourier spectrum. With an increase in the frequency of external force p (p = 1), the attractor becomes more developed and jumps are observed in dynamics from one potential well to another. The Fourier spectrum of such a regime is broadband and does not contain individual peaks, as it was for the previous case. At p = 5, the phase portrait looks even more developed; the phase trajectory visits about 7 potential wells. The Fourier spectrum is also broadband, but in this case a certain higher-amplitude band appears at low frequencies, which corresponds to filtering the signal by the circuit at the resonant frequency. In Table 1 values of the Lyapunov exponents for considered chaotic attractors are presented. The largest Lyapunov exponent for more developed chaotic attractor has the biggest value.

Table 1
Values of the Lyapunov exponents spectrum of harmonic os-
cillator under external periodic force with a controlled phase
(4) for different chaotic attractors.

Parameters	Λ_1	Λ_2	Λ_3
p = 0.25, k = 0.85, A = 8.18	0.018	0.0	-0.118
p = 1, k = 0.57, A = 5.35	0.092	0.0	-0.192
p = 5, k = 3.03, A = 11.1	0.230	0.0	-0.330

Now we turn to the study of the characteristics of the plane of parameters corresponding to the most classical in terms of synchronization: frequency – amplitude of the external signal. As a frequency parameter, we will use the parameter p. Fig. 4 presents charts of the modes of oscillations of system (4) on the plane of parameters (p, A) for various values of the parameter k; the color palette is similar to Fig. 1. Fig. 4a illustrates the structure of the



Fig. 3. Stroboscopic cross sections and Fourier spectra for various chaotic modes of harmonic oscillator under external periodic force with a controlled phase (4). a) p = 0.25, k = 0.85, A = 8.18; b) p = 1, k = 0.57, A = 5.35; c) p = 5, k = 3.03, A = 11.1.



Fig. 4. Charts of dynamical modes of harmonic oscillator under external periodic force with a controlled phase (4) with $\alpha = 0.1$, a) k = 0.5, b) k = 1, c) k = 2.

parameter plane (p, A) at k = 0.5. Here it is possible to distinguish separate zones of complex behavior associated with the so-called resonances at higher harmonics. At low frequencies on the parameter plane, there is a sequence of period doubling bifurcations is observed in the dynamics of the system ending with a transition to chaos. The lines of bifurcations of period doubling have the characteristic form of tongues with a certain threshold in the parameter k. So, for the first line of period doubling (at the maximum frequency of the external signal *p*), the minimum of bifurcation line is located at the doubled resonant frequency, it is typical for the structure of the space of control parameters of a non-autonomous nonlinear oscillator [9–12]. With a decrease in the frequency of forcing, similar lines of period doubling are observed at frequencies corresponding to subresonances. As the frequency decreases, the threshold for bifurcation of the doubling period increases. With an increase in the parameter k, chaos develops due to a decrease in the connectivity of the chaotic attractor, alternating with the appearance of zones of periodic oscillations. On the whole, the structure of the plane of control parameters (Fig. 4a) is similar to that for a non-autonomous nonlinear oscillator [18,19]: it is possible to distinguish separate zones of complex behavior associated with the so-called resonances at higher harmonics.

An increase in the parameter k (Fig. 4b and Fig. 4c) leads to an increase in the range of variation of the phase of the forcing, and as a result to an increase in the regions of complex behavior and the complication of their structure.

Fig. 5 presents charts of dynamic modes on the plane of parameters (p, k) for two values of parameter A: A = 1 and A = 10. Qualitatively, the structure of the parameter plane repeats the analogous one presented in Fig. 4. Which also confirms that a change in the parameters A and k qualitatively leads to the same result. Fig. 5 illustrates the diversity of the zones of existence of various modes of oscillation.

3. Harmonic oscillator under external periodic force with a controlled frequency

The second modification of the model is harmonic oscillator, the frequency of which depends on the dynamical variable. The equation of non-autonomous oscillator in this case has the form

$$\ddot{x} + \alpha \dot{x} + x = A \operatorname{Sin}(p(x)\tau + \phi), \tag{5}$$

where p(x) is the frequency of external force. As in the previous case, we assume that the dependence of the frequency of the



Fig. 5. Charts of dynamical modes of harmonic oscillator under external periodic force with a controlled phase (4) with $\alpha = 0.1$, a) A = 1, b) A = 10.



Fig. 6. Charts of the dynamic modes of harmonic oscillator under external periodic force with a controlled frequency (9) for $\alpha = 0.1$, (a) $p_0 = 0.25$, (b) $p_0 = 1$.

external force on the dynamic variable is linear:

$$p(x) = p_0 + kx(t).$$
(6)

$$\ddot{x} + \alpha \dot{x} + x = A \text{Sin}[(p_0 + kx)\tau + \phi], \qquad (7)$$

Setting $\varphi = 0$, we obtain an equation of the form

$$\ddot{x} + \alpha \dot{x} + x = A \text{Sin}[(p_0 + kx)\tau], .$$
(8)

In the case of frequency control, the dynamics does not change qualitatively; the main difference in the system behavior is the structure of the space of control parameters. A change in the frequency of forcing, which is a consequence of its dependence on a dynamical variable, leads to the fact that the instantaneous frequency of the oscillations changes and the nature of the oscillations is more complex than when controlling the phase. The system of first-order equations in this case has the form:

$$\begin{aligned} x &= y, \\ \dot{y} &= -\alpha y - x + A \text{Sin}(z), \\ \dot{z} &= (p_0 + kx) + ky\tau. \end{aligned}$$

It should also be noted here that, unlike the system of equations (8) in (9), the variable *z* clearly depends on the time τ .

The study of model (9) will be carried out similarly to a controlled phase system. To analyze the dynamics when varying the parameters, we again use the charts of dynamic mode, based on the analyzing the spectrum of Lyapunov exponents.

Fig. 6 shows the charts of the modes of oscillations of system (9) on the plane of parameters (k, A) for various values of the parameter p_0 and the dissipation parameter $\alpha = 0.1$. The color palette used was the same as for Fig. 1. Fig. 6a illustrates the structure of the parameter plane (k, A) at $p_0 = 0.25$. The overall picture remains the same which was for harmonic oscillator under external periodic force with a controlled phase: on the parameter plane, selfoscillation bands with a period of 1 in the stroboscopic section are observed. With basic limit cycles, a cascade of period doubling bifurcations occurs and a chaotic attractor arises. The difference from the case of the dependence of the phase on the variable is that these structures are observed only at small values of the parameters A and k. For large parameter values, the periodicity windows become very narrow and the chaotic dynamics mode dominates. Fig. 6b illustrates the structure of the parameter plane (k, A) with $p_0 = 1$. The structure of the parameter plane remains qualitatively unchanged, bands of periodic regimes are observed, from which chaotic oscillations arise through a cascade of period doubling bifurcations. However, for this choice of parameters, the regions of the limit cycle become more pronounced. With a further increase in the parameter p_0 , the chaos regions disappear and only periodic oscillations are realized in the system. This effect is due to the fact that with an increase in p_0 the amplitude of the forced oscillations decreases, and, accordingly, the amplitude of the change in the forcing frequency.

Fig. 7 shows examples of projections of phase portraits and their stroboscopic sections for the case $p_0 = 0.25$. The phase portrait for the limit cycle of the period-1 is a multi-turn cycle, which



Fig. 7. Two-dimensional projections of phase portraits (red lines) and stroboscopic sections (blue dots) of harmonic oscillator under external periodic force with a controlled frequency (9) for various points of the parameter plane (k, A) at $p_0 = 0.25$. (a) k = 0.02, A = 0.167; (b) k = 0.03, A = 0.2; (c) k = 0.045, A = 0.417; (d) k = 0.085, A = 0.733; (e) k = 0.11, A = 0.9; (f) k = 0.168, A = 1.35; g) k = 0.283, A = 2.267.



Fig. 8. Stroboscopic cross sections and Fourier spectra of harmonic oscillator under external periodic force with a controlled frequency (9) for various chaotic modes. (a) p = 0.25, k = 0.168, A = 1.35; (b) p = 1, k = 0.39, A = 2.77.

corresponds to one point in the stroboscopic section (Fig. 7a). On its basis, a cascade of period-doubling bifurcations occurs. The phase portrait in Fig. 7b corresponds to a double limit cycle; in Fig. 7c, an example of a chaotic attractor is presented. For small values of the parameters A and k, the oscillations occur inside two potential wells of the oscillator, the phase trajectory visits the vicinity of each of the wells. With increasing parameters A and k, a larger number of potential wells are involved in the dynamics of the system. Fig. 7d shows an example of the limit cycle for such a case. The stroboscopic sections shown in Figs. 7e and e clearly show the gradual involvement of more potential wells in the dynamics.

An increase in the frequency parameter p_0 also affects the spectral characteristics of the dynamic mode. Fig. 8 shows examples of phase portraits in the stroboscopic section and Fourier spec-

tra for chaotic attractors at two different values of the frequency parameters p_0 . It is clearly seen in phase portraits that with increasing frequency the attractor becomes more developed and the phase trajectory moves on the basis of a larger number of potential wells. For both cases, the spectrum is broadband, but there is a pronounced component corresponding to the base oscillation frequency. In the case of the regime shown in Fig. 8a, a relatively high uniformity of the spectrum should be noted. Perhaps by the selection of control parameters it can realized chaotic modes with a uniform spectrum.

Next, we consider the structure of other parameter planes for a non-autonomous oscillator, the frequency of which depends on the dynamic variable (9). In Fig. 9 charts of the dynamic regimes of system (9) on the plane of the coefficient of base frequencies ratio vs amplitude parameter of the external force (p_0, A) for various values of the frequency tuning parameter k and the dissipation parameter r = 0.1 are presented. Fig. 9a illustrates the structure of the parameter plane (p_0, A) for k = 1. In the structure of the parameter plane, there is some similarity with Fig. 4a, in the case of controlling the phase of external force, however, there are significant differences. The domain of chaotic dynamics, as well as for the model with phase adjustment, is limited by twice the resonant frequency. In the parameter plane, the structure within which a cascade of period doubling bifurcations with the formation of a chaotic attractor, which is located between the resonant and doubled resonant frequencies, is clearly pronounced. The period doubling bifurcation line has a minimum near the doubled resonant frequency. At a frequency of external force of a lower resonance frequency, at small amplitudes of the impact, periodic self-oscillations are destroyed and a chaotic attractor appears, and there is no set of cascades of period doubling bifurcations corresponding to subresonances, as was in the case with a phase-adapted system. With an increase in the frequency tuning parameter k (k = 1, Fig. 9b), the threshold for the appearance of bifurcation of period doubling near the doubled frequency becomes smaller, the region of chaotic oscillations expands to the domain of high frequencies of external force. Moreover, in the region of more than twice the resonant frequency, new cascades of period doubling are formed at multiple resonant frequencies, but with a large threshold in amplitude. With a further



Fig. 9. Charts of dynamical modes of harmonic oscillator under external periodic force with a controlled frequency (9) with $\alpha = 0.1$, (a) k = 0.5, (b) k = 1, (c) k = 2.



Fig. 10. Charts of dynamical modes of harmonic oscillator under external periodic force with a controlled frequency (9) with $\alpha = 0.1$, (a) A = 1, (b) A = 10.

increase in the frequency tuning parameter k (k = 2, Fig. 9c), the cascade of period doubling bifurcations in the vicinity of the doubled resonant frequency expands to high frequencies and, when it crosses the triple frequency, a uniform region of chaos is formed.

Fig. 10 shows the charts of the dynamic modes of system (9) on the plane of parameters, the coefficient of base frequencies ratio vs frequency control coefficient (p_0, k) for various values of parameter A. Fig. 10a illustrates the structure of the parameter plane (p_0 , k) for A = 1. In the structure of the parameter plane, there is some similarity with Fig. 9a, as well as for the case of controlling the phase of the force. The region of chaotic dynamics is limited by twice the resonant frequency. On the parameter plane, the structure within which a cascade of period doubling bifurcations with the formation of a chaotic attractor, which is located between the resonant and doubled resonant frequencies, is clearly expressed. At a frequency of external force of a lower resonance frequency, for small amplitudes periodic self-oscillations are destroyed and a chaotic attractor appears, and there is no set of cascades of period doubling corresponding to subresonances, as was in the case with a phase-tuning system. At frequencies greater than twice the resonant frequency, periodic self-oscillations are observed. With increasing parameter A = 10 (Fig. 10b), the structure of the parameter plane changes significantly. The period doubling bifurcation threshold near the doubled resonant frequency becomes much smaller. In the vicinity of the tripled resonant frequency, one more period doubling line is observed, with an increase in the frequency tuning parameter k over a wide range of external forcing frequencies, a cascade of period doubling bifurcations is observed and chaotic dynamics appear at frequencies doubled.

4. Experimental implementation

Fig. 11a shows experimental scheme, in which the case of phase controlled harmonic oscillator is implemented. The scheme includes *RLC* circuit, forcing by voltage of the external generator, whose phase depend from capacitor voltage. In experiment we used as generator Adgilent 8115A, spectrum analyzer N9320A and oscilloscope DSO-X4034A. Resonance frequency of the *RLC*-circuit was fixed 330 *kHz*.

The control parameter space of the system under study has a complex structure, but in there dynamics the typical types of behavior are observed. Figs. 11b–e show two-dimensional projections of phase portraits on the plane (U, dU/dt) (upper panel) and power spectra (bottom panel) corresponding period doubling rout to chaos. Also in the dynamics of the system the regimes corresponded to broadband chaos are observed. Fig. 11f shows twodimensional projections of phase portraits on the plane (U, dU/dt) and power spectra corresponding to broadband chaos. Form of phase portraits in physical experiment is similar to the same obtained in numerical simulations.

Fig. 12 shows experimental scheme, in which the case of frequency control is implemented. The scheme include *RLC* circuit, forcing by voltage of the external generator, whose frequency depend from capacitor voltage. The control parameter space in this



Fig. 11. (a) experimental scheme of harmonic oscillator under external periodic force with a controlled phase; (b)–(f) illustrations of formation chaotic dynamics, upper: phase portraits of experimental circuit; bottom: power spectrums.



Fig. 12. a) experimental scheme of harmonic oscillator under external periodic force with a controlled frequency; (b)–(f) illustrations of formation chaotic dynamics, upper: phase portraits of experimental circuit; bottom: power spectrums.

case has complex structure too. In there dynamics period doubling rout to chaos is observed. Figs. 12b–d show two-dimensional projections of phase portraits on the plane (U, dU/dt) (upper panels) and power spectra (bottom panels) corresponding period doubling rout to chaos. Figs. 11e and f show two-dimensional projections of phase portraits and power spectra (on right) corresponding to broadband chaos. Fourier spectrum for broadband chaotic attractors is continuous, but in Fig. 11e it has a pronounced component corresponding to the base oscillation frequency.

5. Conclusion

Thus, the introduction of a linear dependence of the phase and frequency of the external force on the dynamical variable in a nonautonomous linear oscillator can describe property of adaptation a simple system. This property significantly complicates the dynamics of such a simple system and leads to the emergence of a hierarchy of periodic and chaotic oscillations when the control parameters of the external influence are varied. The dynamics of such a system becomes close to a system with multi-well potential.

In the case of phase dependence on the dynamical variable, a hierarchy of chaotic attractors is observed resulting from cascades of period doubling bifurcations, while the lines of period doubling bifurcations are located at the doubled resonant frequency and subresonance frequencies. An increase in the amplitude of the external force leads to the expansion of the domains of existence of complex modes of oscillations and in this case these regions are not limited to twice the frequency of the external influence, as well as the appearance of new zones of periodic oscillations in the region of chaos is observed. In this case, oscillation regimes appear in the dynamics of the system corresponding to the so-called dynamics of a nonlinear oscillator with a periodic potential well.

In the case of the dependence of the frequency on the dynamical variable, a hierarchy of chaotic regimes is also observed, however, only the period doubling line remains in the vicinity of the doubled frequency of the external force. The system of bifurcation lines of period doubling at subresonance frequencies is destroyed with the formation of chaotic dynamics. However, an increase in the frequency of external force in this case also leads to the formation of a picture with a cascade of period doubling and the emergence of a hierarchy of chaotic regimes at the so-called superresonant frequencies.

The chaotic dynamics resulting from the control of the phase and frequency of a dynamic variable is characterized by broadband spectrum. The widest spectrum is observed in the case of a phase dependent on a dynamic variable, with the frequency of the external force near the resonance. For lower frequencies, the pronounced component of the base periodic signal is retained. For lower frequencies of external influence, the signal is filtered by the circuit and the spectrum has a limited band. In the case of a frequency dependence on a dynamical variable, the signal spectra are also broadband, however, the components of the basic limit cycle are pronounced. The results of experimental and numerical studies are in good qualitative agreement.

Declaration of Competing Interest

The authors declare that they have no conflict of interest.

CRediT authorship contribution statement

D.A. Krylosova: Formal analysis, Investigation, Visualization. **E.P. Seleznev:** Conceptualization, Funding acquisition, Supervision, Resources, Writing - original draft. **N.V. Stankevich:** Formal analysis, Investigation, Methodology, Software, Validation, Writing - original draft, Writing - review & editing.

Acknowledgments

This work was supported by the Russian Science Foundation, project No. 17-12-01008. We thank Prof. rer. nat. hab. Marc Timme for fruitful discussion of this problem and an anonymous referee for valuable comments and suggestions that helped us to improve the manuscript.

Appendix

Using *RLC*-circuit presented in Fig. 10a we can write Kirchhoff's voltage law:

$$U_R + U_L + U_C = A\sin(\omega t + \phi), \tag{11}$$

where U_R , U_L , U_C are voltages on the resistor R, inductance L and capacitor C, correspondingly, which can be determined by the next equations:

$$U_R = Ri, \ U_L = Ldi/dt, \ U_C = U.$$
(12)

Here *U* is voltage on the capacitor *C*, which determine current on the capacitor i = CdU/dt. Then we can write Kirchhoff's law in term of dynamical variables of voltage and current:

$$RC\frac{dU}{dt} + LC\frac{d^2U}{dt^2} + U = A\sin(\omega t + \phi).$$
(13)

Simple algebraic transformations give new form of equation:

$$\ddot{U} + 2\gamma \dot{U} + \omega_0^2 U = \frac{A}{\omega_0^2} \sin(\omega t + \phi), \qquad (14)$$

where $2\gamma = \frac{R}{L}$, $\omega_0 = \frac{1}{\sqrt{LC}}$. Then we implement normalization on the frequency, with substitute: $\tau = \omega_0 t$ and get:

$$\ddot{x} + \alpha \dot{x} + x = A \sin(p\tau + \phi) \tag{15}$$

with $x(\tau) = U(t)$, $\alpha = 2\gamma/\omega_0$.

Reference

- Best R. Phase-Lock loops: design, simulation and application. McGraw-Hill; 2007. p. 1–489.
- [2] Shalfeev VD, Matrosov VV. Nonlinear dynamics of phase synchronization systems. Nizhny Novgorod: Publishing House of the Nizhny Novgorod State University; 2013. p. 1–336. (in Russia).
- [3] Leonov GA, Kuznetsov NV, Yuldashev MV, Yuldashev RV. Hold-in, pull-in, and lock-in ranges of PLL circuits: rigorous mathematical definitions and limitations of classical theory. IEEE Trans Circuits Syst Regul Pap 2015;62:2454–64.
- [4] Kuznetsov NV, Leonov GA, Yuldashev MV, Yuldashev RV. Hidden attractors in dynamical models of phase-locked loop circuits: limitations of simulation in MATLAB and SPICE. Commun Nonlinear Sci Numer Simul 2017;51:39–49.
- [5] Ottesen JT. Modelling the dynamical baroreflex-feedback control. Math Comput Model 2000;31:167–73.
- [6] Hall JE. Guyton and Hall textbook of medical physiology e-Book. Elsevier Health Sciences; 2015. p. 1–1147.
- [7] Ponomarenko VI, Prokhorov MD, Karavaev AS, Kiselev AR, Gridnev VI, Bezruchko BP. Synchronization of low-frequency oscillations in the cardiovascular system: application to medical diagnostics and treatment. Eur Phys J Spec Topics 2013;222:2687–96.
- [8] Kiselev AR, Karavaev AS, Gridnev VI, Prokhorov MD, Ponomarenko VI, Borovkova EI, Shvartz VA, Ishbulatov YM, Posnenkova OM, Bezruchko BP. Method of estimation of synchronization strength between low-frequency oscillations in heart rate variability and photoplethysmographic waveform variability. Russ Open Med J 2016;5:e0101–13.
- [9] Karavaev AS, Kiselev AR, Runnova AE, Zhuravlev MO, Borovkova EI, Prokhorov MD, Ponomarenko VI, Pchelintseva SV, Efremova TY, Koronovskii AA, Hramov AE. Synchronization of infra-slow oscillations of brain potentials with respiration. Chaos 2018;28:081102–5.
- [10] Duncan J. An adaptive coding model of neural function in prefrontal cortex. Nat Rev Neurosci 2001;2(11):820.
- [11] Menghini F, van Rijsbergen N, Treves A. Modelling adaptation aftereffects in associative memory. Neurocomputing 2007;70(10–12):2000–4.
- [12] Mongillo G, Barak O, Tsodyks M. Synaptic theory of working memory. Science 2008;319(5869):1543–6.
- [13] Franović I, Omel'chenko OE, Wolfrum M. Phase-sensitive excitability of a limit cycle. Chaos 2018;28(7):071105.

- [14] Verhulst F. Nonlinear differential equations and dynamical systems. Springer Science & Business Media; 2006. p. 1–311.
- [15] Kuznetsov AP, Kuznetsoc SP, Ryskin NM. Nelineynye kolebaniya. Moscow: Fizmatlit; 2006. p. 1–292. (in Russia).
- [16] Holmes P. A nonlinear oscillator with strange attractor. Phylos Trans 1979;292:419–48.
- [17] Humieres DD, Beasley MR, Huberman BA, Libhaber A. Chaotic states and rout to chaos in forced pendulum. Phys Rev A 1982;26:3484–96.
- [18] Holmes P, Whitley D. On attracting set of Duffing's equation. Physica D 1983;7:111–23.
- [19] Sato S, Sano M, Sawada Y. Universal scaling property in bifurcation structure of Duffing's and generalized Duffing's equation. Phys Rev A 1983;28:1654–8.
- [20] Awrejcewicz J. Gradual and sudden transition to chaos in a sinusoidally driven nonlinear oscillator. J Phys Soc Japan 1989;58(12):4261–4.
- [21] Englisch V, Lauterborn W. Regular window structure of a double-well Duffing's oscillator. Phys Rev A 1991;44:916-24.
- [22] Awrejcewicz J. Chaos in simple mechanical systems with friction. J Sound Vib 1986;109:178–80.
- [23] Awrejcewicz J. Chaotic motion in a nonlinear oscillator with friction. KSME J 1988;2(2):104–9.
- [24] Awrejcewicz J, Pyryev Y. Chaos prediction in the duffing-type system with friction using Melnikov's function. Nonlinear Anal Real World Appl 2006;7(1):12–24.
- [25] Wei M, Han X, Zhang X, Bi Q. Bursting oscillations induced by bistable pulse-shaped explosion in a nonlinear oscillator with multiple-frequency slow excitations. Nonlinear Dyn 2019:1–12.
- [26] Toda M. Studies of a non-linear lattice. Phys Rep 1975;18:1-123.
- [27] Kurz Th, Lauterborn W. Bifurcation structure of the Toda oscillator. Phys Rev A 1988;37:1029–31.
- [28] Astakhov VV, Bezruchko BP, Seleznev EP. Investigations of the dynamics of an oscillatory circuit under harmonic excitation. Radiotekhnika i Elektronika 1987;32:2558–66 (in Russia).
- [29] Bezruchko BP, Seleznev EP. Complex dynamics of a driven oscillator with a piecewise-linear characteristic. Tech Phys Lett 1994;20:800–1.
- [30] Bezruchko BP, Prokhorov MD, Seleznev EP. Multiparameter model of a dissipative nonlinear oscillator in the form of one-dimensional map. Chaos, Solitons Fractals 1995;5:2095–107.
- [31] Seleznev EP, Zakharevich AM. Structure of the control parameter space for a nonautonomous piecewise linear oscillator. Tech Phys 2006;51:522–4.
- [32] Geist K, Lauterborn W. The nonlinear dynamics of the damped and driven toda chain: 1. energy bifurcation diagrams. Phys D 1988;31:103–16.
- [33] Geist K, Lauterborn W. The nonlinear dynamics of the damped and driven Toda chain: 2. fourier and lyapunov analysis of Tori. Phys D 1990;41:1–25.
- [34] Geist K, Lauterborn W. The nonlinear dynamics of the damped and driven Toda chain: 3. classification of the nonlinear resonances and local bifurcations. Phys D 1991;52:551–9.

- [35] Astakhov VV, Bezruchko BP, Kuznetsov SP, Seleznev EP. Onset of quasiperiodic motions in a system of dissipatively coupled nonlinear oscillators driven by a periodic external force. Sov Tech Phys Lett 1988;14:16–18.
- [36] Kozlowski J, Parlitz U, Lauterborn W. Bifurcation analysis of two coupled periodically driven duffing oscillators. Phys Rev E 1995;51:1861–967.
- [37] Kuznetsov AP, Stankevich NV, Tyuryukina LV. The death of quasi-periodic regimes in a system of dissipatively coupled van der pol oscillators under pulsed drive action. Tech Phys Lett 2008;34:643–5.
- [38] Kuznetsov AP, Seleznev EP, Stankevich NV. Nonautonomous dynamics of coupled van der Pol oscillators in the regime of amplitude death. Commun Nonlinear Sci Numer Simul 2012;17:3740–6.
- [**39**] Dvorak A, Kuzma P, Perlikowski P, Astakhov V, Kapitaniak T. Dynamics of three Toda oscillators with nonlinear unidirectional coupling. Eur Phys J Spec Topics 2013;222:2429–39.
- [40] Stankevich NV, Dvorak A, Astakhov V, Jaros P, Kapitaniak M, Perlikowski P, Kapitaniak T. Chaos and hyperchaos in coupled antiphase driven Toda oscillators. Regul Chaotic Dyn 2018;23:120–6.
- [41] Josephson BD. Possible new effects in superconductive tunnelling. Phys Lett 1962;1:251–3.
- [42] Salam F, Sastry S. Dynamics of the forced JOSEPHSON junction circuit: the regions of chaos. IEEE Trans Circuits Syst 1985;32:784–96.
- [43] Cawthorne AB, Whan CB, Lobb CJ. Complex dynamics of resistively and inductively shunted Josephson junction. J Appl Phys 1998;84:1126–32.
- [44] Dana SK. Chaotic dynamics in Josephson junction. IEEE Trans Circuits Syst-I 2001:48:990–6.
- [45] Simo H, Domguia US, Dutt JK, Woafo P. Analysis of vibration of pendulum arm under bursting oscillation excitation. Pramana 2019;92(1):3.
- [46] Sprott JC, Hoover WG. Harmonic oscillators with nonlinear damping. Int J Bifurc Chaos 2017;27 1730037-19.
- [47] Tang YX, Khalaf AJM, Rajagopal K, Pham VT, Jafari S, Tian Y. A new nonlinear oscillator with infinite number of coexisting hidden and self-excited attractors. Chin Phys B 2018;27:040502–6.
- [48] Jahanshahi H, Rajagopal K, Akgul A, Sari N N, Namazi H, Jafari S. Complete analysis and engineering applications of a megastable nonlinear oscillator. Int J Non Linear Mech 2018;107:126–36.
- [49] Vo TP, Shaverdi Y, Khalaf AJM, Alsaadi FE, Hayat T, Pham VT. A giga-stable oscillator with hidden and self-excited attractors: a megastable oscillator forced by his twin. Entropy 2019;21 535-14.
- [50] Seleznev EP, Stankevich NV. Complex dynamics of a non-autonomous oscillator with a controlled phase of an external force. Tech Phys Lett 2019;45:57–60.
- [51] Pikovsky A, Politi A. Lyapunov exponents: a tool to explore complex dynamics. Cambridge University Press; 2016.
- [52] Benettin G, Galgani L, Giorgilli A, Strelcyn JM. Lyapunov characteristic exponents for smooth dynamical systems and for Hamiltonian systems; a method for computing all of them. Part 1: Theory Meccanica 1980;15(1):9–20.